



# Service Bulletin


Bulletin No.: 20-NA-127

Date: June, 2020

## TECHNICAL

**Subject: Rear Brake Lights Stay Illuminated All the Time**

Brand:	Model:	Model Year:		VIN:		Engine:	Transmission:
		from	to	from	to		
Chevrolet	Bolt EV	2017	2020	—		All	All

<b>Involved Region or Country</b>	North America, Middle East, Europe, GM Korea Company
<b>Condition</b>	Some customers may comment that the rear brake lights stay on all the time and/or stay on while the vehicle is turned off.
<b>Cause</b>	<div style="text-align: center;">  </div> <p style="text-align: right; font-size: small;">5608493</p> <p>The cause of the condition may be a loose/damaged X200 connector at the left A-Pillar near the floor.</p>
<b>Correction</b>	Test for a loose connection at the connector to see if the brake lights will turn on/off. If found to be loose, repair the connection at the X200 connector.

## Service Procedure

If you encounter a vehicle with the above concern, remove the front side door sill garnish molding and move the harness above the X200 before unplugging to see if the brake lights come on or flicker. Refer to *Front Side Door Sill Garnish Molding Replacement* in SI. Open the connector and inspect for internal damage to the connector and terminals.

- If the X200 connector is not fully seated or damaged, repair as necessary.
- If the X200 connector is fully seated and no damage can be found, continue diagnosis referring to SI.

## Parts Information

No parts are required for this repair.

## Warranty Information

For vehicles repaired under warranty, please use the appropriate warranty labor operation based on the actual cause and repair.

Version	1
Modified	Released June 04, 2020

