

Enabling “Transport Mode” for eGen SOC.

1. On the main screen press and hold the “OK” button



2. This will send you to the Application Status screen. Here you will press and hold the F4 button labeled “TRANS”



- This will send you into the “Transportation Mode”. The current SOC Reserve limit will be displayed at the top. On this screen you will select F3 “60%”



- After the selection, the screen will state “Please Wait...” and then go to the main screen with “TRANSPORT” in red lettering.



In this mode, your battery system will turn off at 60% state of charge.

Disabling “Transport Mode” for eGen SOC.

1. On the main screen, you will notice that the word “TRANSPORT” will be in red. This means the system is in transport mode and will turn off at the 60% overall state of charge. To take the system out of transport mode for final delivery to the client, on the main screen, press and hold the “OK” button



2. This will send you to the Application Status screen. You will press and hold the F4 button labeled “TRANS.”



- This will send you into the “Transportation Mode”. At the top, you will see the “SOC Reserve limit” currently displayed in transport mode 60; press F1 to select 10%. After the selection, you will be prompted with “Please Wait...”



- After the selection, you will be sent to the main screen



This should be the state that the system should be set to when it is delivered to the owner.